Lenovo S400z Platform Specifications

Processor	Intel® Pentium® or 6th Generation Intel Core™ i3 / i5 / i7 Processor						Keyboard	Some: Lenovo Slim USB Keyboard (USB connector), black or white				
	Processor Cores / Frequency Threads Base/Max(GHz) Cache Memory Types Integrated Graphics						Mouse	Some: Ultraslim Plus Wireless Keyboard (2.4GHz via USB receiver), black Nouse Some: Optical USB Mouse, black or white, Lenovo logo Some: Ultraslim Plus Wireless Mouse (2.4GHz via USB receiver), black				
	Pentium 4405U Core i3-6100U	2/4	2.1 G 2.3 G	2 MB 3 MB	DDR4-2133 DDR4-2133		Mechanical	Black or white color				
	Core i5-6200U 2 / 4 2.3 G / 2.8 G 3 MB DDR4-2133 HD 520							Support VESA mount (100mm)				
	Core i7-6500U	2/4	2.5 G / 3.1 G	4 MB	DDR4-2133	HD 520			Dimensions (WxDxH)	Max weight (lb / kg)	Adjustments	
	Intel Architecture controller, and I/0	O interfac	es into a single s	System-o	n-Chip solution			Without stand:	21.0 X 1.6 X 14.8 (inch); 535.2 X 40 X 375.7 (mm)	13.0 / 5.9	N/A	
Memory	16GB max, DDR4 2133, two 260-pin SO-DIMM sockets, dual-channel capable							With Frame	21.0 X 2.5 X 15.1 (inch);	14.0 / 6.36	Tilt: 15° to 40° back	
Disk	Some: SATA 6.0Gb/s, 2.5" Wide, 5400 rpm or 7200 rpm Some: Solid State Hybrid Drive (SSHD) / with 8GB MLC NAND flash memory, SATA 6.0Gb/s, 2.5" Wide, 5400 rpm Some: Solid State Drive (SSD) / SATA 6.0Gb/s, 2.5" Wide Some: DVD burner, SATA 1.5Gb/s, 9.5mm high							stand With Monitor stand:	535.2 X 63.7 X 382.7 (mm) 21.0 X 9.0 X 17.2 (inch); 535.2 X 227.9 X 435.7 (mm	16 1 / 7 21	Tilt: 24° back, -5° forward	
Optical Media reader							Power supply	90 watts external adapter, autosensing, 88% PSU				
Media reader Graphics	6-in-1 media card reader Intel HD Graphics 510/520 in processor, uses main memory, DirectX® 12, external monitor support via HDMI; Max resolution: 2560x1600 (HDMI)@60Hz 21.5" (546.1mm) Full HD 1080p (1920x1080), viewing angle (horizontal: +/- 85°; vertical: +/- 80°), LED backlight, 250 nits, 16:9 aspect ratio, 1000:1 contrast ratio, frameless design None						Limited warranty ³	Some: 1-year or 3-year, depot repair service Some: 1-year or 3-year, limited onsite service For Lenovo service upgrade options, please go to S-TC sheet				
Display Light sensor							Preload	Preloaded operating system Some: Windows 10 Pro 64-bit Some: Windows 10 Home 64-bit Some: Windows 7 Professional 64 preinstalled through downgrade rights				
Multi-touch	None								dows 10 Pro 64-bit olications (only some listed)			
Camera	1.0-megapixel camera, fixed focus, supports 720p, with digital						 Lenovo Resc 	ue System (
Controls	microphone, LED indicator, physical switch on/off Power on/off button							 Driver and Application Installation Lenovo Solution Center Lenovo Bluetooth Lock Lenovo SHAREit McAfee® LiveSafe™ (30-day trial) Microsoft® Office preloaded; purchase a product key to activate Lenovo Companion (Win10 only) Adobe® Reader® (Win7 only) 				
Chipset	Intel System-on-Chip (SoC) platform						-					
Rear ports Side ports M.2 card slot	Three USB 2.0, ethernet (RJ-45), HDMI out port Two USB 3.0, optional card reader, headphone / microphone combo jack (3.5mm) One M.2 Card slot (for WLAN)											
Audio support	High Definition (HD) Audio, Realtek ALC233 / two internal speakers (3W x 2)						-					
WLAN ¹³	Some: 11ac wireless, M.2 Card, Qualcomm Atheros QCA9377 (dual band), Wi-Fi + Bluetooth 4.1 combo adapter, 1x1 Some: 11ac wireless, M.2 Card, Qualcomm Atheros QCA6174 (dual band), Wi-Fi + Bluetooth 4.1 combo adapter, 2x2 Some: 11ac wireless, M.2 Card, Intel Dual Band Wireless-AC 3165, Wi-Fi + Bluetooth 4.0 combo adapter, 1x1											
							Environment	ENERGY STAR® 6.1 (Need 85% PSU and Windows OS); ErP Lot 3; GREENGUARD®; RoHS-compliant				
							Accessories	For compatible accessories, please go to http://www.lenovoquickpick.com/				
Bluetooth™ Ethernet	Some: Bluetooth One gigabit ethe					combo adapter						
Manageability Security chip	None None											
Security features	 Security slot (in optional Kensir Kensington loc Smart USB promouse only, block 	ngton® Mi k also loc otection, a	croSaver® cable; ks chassis) allows keyboard/	Boot sBoot v	r-on, admin, hard sequence control vithout keyboard dual USB port dis	and mouse						